



PMX-164

Order No.: 0203150

Price upon request

PRODUCTINFOS

Powered mixer, 70 W, 4 Ω

- Audio mixer and audio amplifier built into a wooden housing with black felt covering
- 5 mono input channels, each with gain control, 2-way tone control and effect control
- 1 mono input channel (stereo input) with gain control, 2-way tone control and effect control
- Integrated Bluetooth receiver
- Integrated MP3 player with USB port, SD card slot and illuminated LCD
- Adjustable digital delay
- Tape record and CD/tape play connections
- 5-band graphic equalizer
- Low-pass filter: 200 Hz, 6 dB/oct.
- Sub-out output for connecting an active subwoofer

TECHNICAL SPECIFICATIONS

PMX-164

No. of channels

6

PMX-164

No. of inputs	13
Mic input	1.5 mV, bal., 6 x 3-pole XLR 15 mV, bal., 5 x 6.3 mm jack,
Line input	85 mV, 1 x RCA L/R, 550 mV, 1 x 6.3 mm jack
Tape (play)	200 mV, 1 x RCA L/R
Monitor output	7.5 V, 1 x 6.3 mm jack (sub out)
Tape (rec)	550 mV, 1 x RCA L/R
Frequency range	20-20,000 Hz
THD	0.1%
S/N ratio	> 65 dBA
Equalizer bass	± 15 dB/80 Hz
Equalizer treble	± 15 dB/10 kHz
equalizer	± 12 dB, 100/500 Hz/1/2.5/10 kHz
Amplifier	Power rating 2 x 40 W/4 Ω , 2 x 30 W/8 Ω Peak music power output 2 x 70 W/4 Ω , 2 x 50 W/8 Ω
Power supply	~ 230 V/50 Hz/210 VA
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	210 VA
Admiss. ambient temp.	0-40 $^{\circ}$ C
Width	400 mm
Height	220 mm
Depth	230 mm
Weight	7 kg